

# Smart Dongle-4G



## Smart

4G communication <sup>1</sup>

Support 3rd-party monitoring system <sup>2</sup>



## Simple

Plug & Play

WLAN-AP for local deploying <sup>3</sup>



## Reliable

IP65

Support auto reconnection

Technical Specification	SDongleB-06-EU	SDongleB-06-AU	SDongleB-06-NH
-------------------------	----------------	----------------	----------------

General Data	
Max. Devices Supported	10
Max. Inverters Supported	10
Connection interface	USB
Installation	Plug-and-play
Indicator	LED Indicator
Dimensions (W * H * D)	162*48*28mm
Degree of protection	IP65
Power consumption (typical)	3.5W

Wireless Parameter			
Sim card type	mini-sim (15 mm*25 mm)		
Supported standards & frequencies <sup>4</sup>	LTE-FDD: B1/B3/B7/B8/B20/B28 LTE-TDD: B38/B40/B41 GSM: 850/900/1800/1900MHz	LTE-FDD: B1/B2/B3/B4/B5/B7/B8/B28 LTE-TDD: B40 WCDMA: B1/B2/B5/B8 GSM: 850/900/1800/1900MHz	LTE-FDD: B1/B3/B8/B18/B19/B26 LTE-TDD: B41 WCDMA: B1/B6/B8/B19
Wifi Operation Mode	AP		
Supported standards & frequencies	802.11b/g/n (2.412G—2.484G)		

Environment	
Operating temperature range	-30 °C to +65 °C (-22 °F to 149 °F)
Relative humidity range	5 - 95% RH
Storage temperature range	-40 °C to +70 °C (-40 °F to 158 °F)
Max. operating altitude	4,000 m (13, 123 ft.)

Standard Compliance (more available upon request)			
Certificate	CE	RCM	TELEC

Inverter Compatibility	
Inverter model	SUN600-5/6KTL-L0 SUN2000-2~6KTL-L1 SUN2000-3~10KTL-M1 SUN2000-8~20KTL-M2 SUN2000-12~25KTL-M5 SUN2000-20~50KTL-M3 SUN2000-50/60KTL-M0 SUN2000-50KTL-JPM1 SUN2000-63KTL-JPM0 SUN2000-75KTL-M1 SUN2000-100KTL-M0/M1 SUN2000-100KTL-INM0 SUN2000-110KTL-INM2 SUN2000-100/115KTL-M2

1: To ensure stable data transmission, Huawei suggests 4G dongle to be installed in areas with stable mobile signal (2G signal ≥4 bars, 3G/4G signal ≥3 bars).  
 2: 3rd-party management system shall match the communication protocol with Huawei Smart Dongle.  
 3: When all inverters support WLAN hotspot, hotspot of Dongle will be disabled by default.  
 4: For recommended carriers list and details on supported frequencies, please contact local distributors.